



Heavy-Duty 4300 Watt Gas Generator - DG4300

FEATURES

- Honda 8 HP, OHV GX engine provides jobsite reliability
- Maintenance free, brushless alternator for increased durability
- High amp surge capacity ideal for starting high amp tools including air compressors
- Maximum 120V power switch ensures peak performance of 120 and 240 volt tools
- Jobsite tested frame with panel protection bars for increased durability
- Super quiet muffler reduces engine noise
- Idle control saves fuel and reduces noise
- Low oil shut-off protects engine
- Dry Weight and dimensions do not include accessories

SPECIFICATIONS

Max AC Output	4300 watts
Rated AC Output	3800 watts
Max Current (120V/240V)	35.8/17.9 amps
Alternator Type	Brushless
Rated Current (120V/240V)	31.7/15.9 amps
Honda GX Engine	8 HP
Fuel Tank Capacity	5 gal
120 Volt GFCI Receptacles (20 Amp)	4
120 Volt GFCI Twist Locking Receptacle (20 Amp)	1
120 Volt Twist Locking Receptacle (30 Amp)	0
120V/240V Twist Locking Receptacle (20 Amp)	1
120V/240V Twist Locking Receptacle (30 Amp)	0
Decibel, idle up (calculated 7 yards from unit)	70 dBA
Run-Time [@ 50% Maximum Output]	11.1 hrs
Tool Length	24.4 "
Tool Width	21.7 "
Tool Height	20.1 "
Dry Weight	159 lbs
Shipping Weight	214 lbs
Starting System	Recoil